


1. Be sure that Callisto is charged more than 30%.
2. Plug Callisto 100 to your PC via special USB cradle
3. Copy "**iconBIT-ota-user.user.zip**" to root folder of internal memory storage of Callisto 100(do not extract it)
4. Unplug your watches from PC
5. Check the presens of "**iconBIT-ota-user.user.zip**" file in root folder of Callisto 100. Use File Explore.
6. Go to Settings->System->Accessibility ->disable Quick Boot option
7. Turn off you Callisto 100
8. Wait about 10 seconds
9. Press and hold HOME button than press and hold POWER button
10. Hold both button untill recovery messages apper:
 - a. => Power For RECOVERY MODE
 - b. => Home For FACTORY MODE
11. If no recovery menu wiil appear and screen will be dimmed, wait 10 seconds and try again from 9 point. If no recovery menu will appear and you will see iconBIT logo, wait till device will be fully loaded than turn it off.
12. Choose RECOVERY MODE and press POWER button
13. Wait till Green Android logo will appear
14. Press POWER button
15. You will se recovery screen



16. Use HOME button for navigation and POWER button to select operation. To return to previous point use "/" point
17. Backup your used data using «backup user data» option. Afterwards you will be able to restore your data using «restore user» data option.
18. Clear cache of Callisto 100 usiong «Wipe cache partiotion» option
19. Choose «apply update from sdcard» option and select «iconBIT-ota-user.user.zip» file. After successful upgrade you will see «Install from sdcard complete» message.
20. Wipe chache again
21. Upgrade complete
22. Select «reboot system now», wait untill Android OS will be loaded.
23. Delete "**iconBIT-ota-user.user.zip**" file from internal memory of your Callisto 100
24. End